


## Black Opal Xtreme Air 19 Airborne Special Flat Panel Display System





### **TABLE OF CONTENTS**

Chapter	- LA/	Page
1 DESCRIPTION	AL ALL	1-1
2 SPECIFICATIONS		2-1
2.1 System Performance		2-1
2.2 Controls		2-4
2.3 Communications		2-4
2.4 Physical Characteristics		2-5
2.5 Electrical Requirements	-	2-5
2.6 Environmental	1	2-5
2.7 Connector/Pin Details		2-6
3 SET-UP		3-1
3.1 Mounts		3-1
3.2 Connections		3-1
3.3 Set-up Procedure		3-2
3.4 Heating and Cooling		3-3
4 OUTLINE DRAWING		4-1
LIST OF FIGURES		
Figure 3-1: Mounts		3-1
Figure 3-2: Connections		3-2
Figure 4-1: Outline Drawing		4-1



File: <b>PS-RMU-S-1680-A_1</b>	Author(s): TW	Authorised: TW	Rev. Date: 11.3.14	Page i



### Black Opal Xtreme Air 19 Airborne Special Flat Panel Display System

#### 1 DESCRIPTION

Laserdyne's Black Opal displays have been engineered for a wide range of land-, sea- or air-borne display applications including remote/indirect viewing of video images generated by day, night or thermal cameras.

The Xtreme Air 19 model is a 19" [with SXGA (1,280 x 1,024) resolution] version of the Black Opal display type, specially designed for airborne use.

This is a reduced weight/reduced cost model, where some of the stringent sealing and other measures required for land and seaborne operations have been relaxed. It retains the advanced video features and generally high level of ruggedisation for which Black Opal displays are renowned.

This model is fitted with a high brightness LED backlight module. LED backlighting improves reliability when compared with standard CCFL (lamp) backlights – not only by substituting solid-state components for fragile lamps, but also by the graceful nature of LED backlight degradation as the unit ages – a missing lamp may make an LCD unreadable, but a few fading LEDs make little difference.

Each Xtreme Land model consists of a LED backlit LCD, a low reflection high clarity window, a microprocessor unit, and power & control electronics. All items are housed within a rugged enclosure containing heating and cooling mechanisms. The LCD is protected by a tough, antireflection-coated window which also provides EMI/EMC shielding. The window is matched to the LCD glass with index-matched materials to minimise internal reflections, eliminating potential internal window fogging and maximising window strength. All models are button operated.

Each model features MultiVision, allowing for multiple analogue and SDI video inputs (for SD, HD and other analogue video formats, and PC RGB inputs), and providing simultaneous display of up to 6 inputs.

Images are displayed on a LED backlit LCD that may be viewed in full direct sunlight down to full darkness and feature backlight settings suitable for low light viewing, for viewing with Night Vision Devices and completely off for black-out conditions.

Black Opal displays have several features designed to increase the effectiveness of surveillance, sighting and security systems, including:

Image Enhancement: video inputs are compensated for obscuration (e.g. rain, fog, snow, mist or smoke) within an adjustable central window where contrast and colour are enhanced. For a chosen window size, the enhancement is applied to that portion of the <u>displayed</u> image;

Digital Zoom: a fully X & Y interpolated "smart" zoom, not merely pixel multiplying, yields a clear zoomed image without the blocky "pixelated" appearance often seen with digital zooming; and

Freeze Frame: freezes the current prime video channel while leaving live any video inset.

Colourisation: applies preloaded colour palettes to monochrome imagery.

Motion ("edge tearing") compensation: minimises the jagged edges that can occur with motion in video on LCDs.

These displays also provide overlay (chroma keying) capability.

Black Opal display software is easily upgradeable, upgrades can be downloaded in the field via a PC.



File: <b>PS-RMU-S-1680-A_1</b>	Author(s): TW	Authorised: TW	Rev. Date: 11.3.14	Page  1-1



## Black Opal Xtreme Air 19 Airborne Special Flat Panel Display System

#### **2 SYSTEM SPECIFICATIONS**

Notation - use of brackets in tables: [notes & qualifications] (units) {alternate units}.

### 2.1 System Performance

PARAMETER		SPECIFICATION
	Designa	tion
Xtreme Air 19		Black Opal airborne special - helicopter- dedicated design, 19", high brightness, SXGA resolution
	Contr	ol
Control Functions [factory configure customer requirements]	able to	On/Off; backlight intensity; menu select; select screen lay-out; select image enhancement feature; digital zoom; freeze frame; night day toggle
Controls		9 tactile LED-backlit (green or red selectable) buttons
	Displa	ау
Туре		Active Matrix Colour (24-bit colour) LED backlit LCD Module
Display Size (" {cm})	diagonal	19 {48.3}
	active area	14.8 {37.6} x 11.85 {30.1}
Aspect Ratio [width:height]		5:4
Pixel Number [1 pixel is RGB trio]	The second second	1,280 x 1,024
Colour		16 million [8-bit each colour]
Grey Scale	A	256 [8-bit]
Backlight Luminance [LED type;	minimum	0
approx.; adjustable] (cdm <sup>-2</sup> ) <sup>1</sup>	maximum	1,000
Contrast Ratio [limiting; LCD]		800:1
Response Time [typical] (ms)		6 [T <sub>r</sub> =4; T <sub>f</sub> = 2]
Readability [ambient conditions]		black-out to full direct sunlight [105 lux]
Night Vision Device compatible?		yes [low intensity green; red selectable]
Viewing Angle	vertical	±80
[full angle] (°)	horizontal	±80

<sup>&</sup>lt;sup>1</sup> 1 cdm<sup>-2</sup> = 1 nit.



File: <b>PS-RMU-S-1680-A_1</b>	Author(s): TW	Authorised: TW	Rev. Date: 11.3.14	Page 2-1



# Black Opal Xtreme Air 19 Airborne Special Flat Panel Display System

PARAMETER		SPECIFICATION	
	Inputs		
	Low resolution group	4 simultaneous channels, each channel being either 1 x Y/C or 2 x CVBS	
Physical Connections	High Resolution group	1 simultaneous channel, selectable from 6 general purpose analogue inputs. Connections supported are 6 x CVBS, or 3 x Y/C, or 2 x YPrPb, or 2 x RGsB, or 2 x RGBHV.	
	SDI group	1 simultaneous channel, selectable from 2 inputs	
	Low resolution group	Standard definition (SD) only: (PAL/NTSC/SECAM/CCIR-601/RS170; interlaced and non-interlaced)	
		SD using CVBS or Y/C: (PAL/NTSC/SECAM/CCIR-601/RS170; interlaced and non-interlaced)	
Signal Formats supported	High Resolution	HD using YPrPb or RGB: (720p, 1080i, 1080p);	
\	group	PC RGB input: VESA RGB analogue (UXGA maximum resolution)	
		Other analogue video standards supported on request (i.e. STANAG 3350)	
flee 1	SDI group	SMPTE 259M, SMPTE 292M (SMPTE 424M optional)	
	Low	CVBS, Y/C.	
	resolution group	All analogue inputs are 75ohm terminated	
Connection Formats	High	CVBS, Y/C, YPrPb, RGBHV, RGsB.	
	resolution group	All analogue inputs are 75ohm terminated.	
	SDI group	SD-SDI, HD-SDI (3G-SDI optional). BNC, 75 ohm.	
	Output	s	
	Analogue	1 output channel, available from 3 general purpose analogue outputs. Connections supported are SD: (CVBS and Y/C simultaneous) or RGB or YPrPb; or	
Physical Connections	output group	HD: YPrPb or RGB or	
,		PC: RGBHV/RGsB [XGA maximum resolution]	
		All analogue outputs are 75ohm	
	SDI output group	2 x BNC, 75ohm	

File: <b>PS-RMU-S-1680-A_1</b>	Author(s): TW	Authorised: TW	Rev. Date: 11.3.14	Page 2-2



# Black Opal Xtreme Air 19 Airborne Special Flat Panel Display System

PARAMETER		SPECIFICATION
Signal Formats supported	Analogue output group	SD: PAL/NTSC/SECAM/CCIR-601/RS170 HD: SMPTE 274M 1080p30, 1080i60, 720p60 (maximum resolution) PC: VESA (XGA maximum resolution)
	SDI group	SMPTE 259M, SMPTE 292M (SMPTE 424M optional)
	Analogue output group	CVBS, Y/C, YPrPb, RGBHV, RGsB
Connection Formats		Output 1: Re-clocked copy of the selected SDI input channel (same format as the input)
	SDI group	Output 2: Configurable to be either (a) any other video input (same format); or (b) A specified format
	Analogue output group	Configurable to be either (a) pass through any other video input (with a compliant format); or (b) a specified format and image configuration using any of the available inputs (limits apply)
Functionality	7	Output 1: Re-clocked copy of the selected SDI input channel (same format as the input)
	SDI group	Output 2: Configurable to be either (a) pass through any other video input (with a compliant format); or (b) a specified format and image configuration using any of the available inputs (limits apply)
	Safety & Pro	tection
Cooling		thermal transfer by internal and external convection
Display Window	T	Antireflection, hard-coated, sealed, EMI/EMC shielded; index-matched to LCD glass
		conforms to:
		QSTAG 307;
		MIL-STD-704E;
		MIL-STD-1275D;
Electrical Protection		STANAG 3350 (all analogue video inputs)  RTCA/DO-160D, Category Z, power input 18 to 30.3Vdc [min. max. & emergency operation, interrupts, abnormal surge (48Vdc for 1s), engine starting undervoltage];
		RTCA/DO-160D, Category A, voltage spike [600Vdc for 10μs]



File: <b>PS-RMU-S-1680-A_1</b>	Author(s): TW	Authorised: TW	Rev. Date: 11.3.14	Page 2-3



## Black Opal Xtreme Air 19 Airborne Special Flat Panel Display System

PARAMETER		SPECIFICATION
Audible Emission [@ ≥ 10m]		nil
	Suppo	rt
MTBF [@30°C; 100%	Ground Mobile [wheeled]	> 14,700
duty cycle] (hours)	Airborne Rotary Wing	> 6,500
Operational Life (years)		10

#### 2.2 Controls

Control Type	Loca	ation	Primary Label	Primary Function
Button		left	Ů	toggle between active and standby
Button		2 <sup>nd</sup> left		menu
Button		3 <sup>rd</sup> left		show assigned screen lay-outs for selection
Button	bottom of	4 <sup>th</sup> left		enhance
Button	bottom of front face	centre		zoom
Button	HOIR IACE	4 <sup>th</sup> right	TEXAS	freeze
Button		3 <sup>rd</sup> right	$\nabla$	backlight down; scroll/adjust down
Button	//	2 <sup>nd</sup> right	Δ.	backlight up; scroll/adjust up
Button	flee	right	<b>\$</b>  (	toggle between Day and Night backlight modes

#### 2.3 Communications

PARAMETER		SPECIFICATION
Ports		three Serial ports (maximum)
Data	Format	2 x RS-232, 1 x RS-422 (other configurations available on request – maximum capacity is 2 x RS422 or 4 x RS232)
	Rate (Baud)	115200,n,8,1 standard, others available on request



File: <b>PS-RMU-S-1680-A_1</b>	Author(s): TW	Authorised: TW	Rev. Date: 11.3.14	Page 2-4



## Black Opal Xtreme Air 19 Airborne Special Flat Panel Display System

### 2.4 Physical Characteristics

PARAMETER			SPECIFICATION
Mass [approx.] (kg)			< 7.6
Dimensions	Width	body	433
(mm)		overall <sup>2</sup>	453
	Height	body	353
		overall <sup>2</sup>	373
	Depth <sup>3</sup>	body	63.3
		overall <sup>2</sup>	77.95
Mounting	Pa	anel Mount	8 x 5.5mm diameter holes in corners, 4 per side
	S	ide Mount	2 x M6 tapped holes, 8mm deep, on each side

#### 2.5 Electrical Characteristics

PARAMETER		SPECIFICATION		
Supply Voltage (Vdc) [MIL-STD-7	04C]	18 to 33 [28 nominal]		
Current Drain	heater on	ILEANS < 8		
[@ 28Vdc; typical] (A)	heater off	< 3		

### 2.6 Environmental

PARAMETER				SPECIFICATION
Temperature (°C)	Operate <sup>4</sup>	min. <sup>5</sup>		-25
[RTCA/DO-160D,		max. <sup>6</sup>	long term	+55
class A1]			short term	+70
	Survive		min. <sup>5</sup>	-40
			max. <sup>6</sup>	+85
Vibration [RTCA/DO-160D, Helicopter Category R]			sine on random	

<sup>&</sup>lt;sup>2</sup> Including mounting flange.



File: PS-RMU-S-1680-A_1	Author(s): TW	Authorised: TW	Rev. Date: 11.3.14	Page 2-5

<sup>&</sup>lt;sup>3</sup> Excluding connectors.

<sup>&</sup>lt;sup>4</sup> When used in accordance with procedures in User's Manual.

<sup>&</sup>lt;sup>5</sup> Without wind-chill.

<sup>&</sup>lt;sup>6</sup> Without solar radiation.



# Black Opal Xtreme Air 19 Airborne Special Flat Panel Display System

PARAMETER		SPECIFICATION
Shock [RTCA/DO-160D,	operational	6g, 11ms; 3 shocks in each orientation
Helicopter Categories B & C, drop shock]	crash safety	20g, 11ms; 3 shocks in each orientation
Sealing [RTCA/DO-160D, Cate	gory W] <sup>7</sup>	water resistant [drip proof]
Altitude/Low Pressure [operational; RTCA/DO-160D, class A1]		15,000 feet
EMI/EMC 7,8		RTCA/DO-160D; MIL-STD-461D

#### 2.7 Connector/Pin Details

No.	Name	Pin Marking	Purpose	Notes for Harness
J1: I	Power & Comms C	onnection	: Connector, MilSpec, 38999/ screw-on, 13 Way	/24WB35PN, 11-35, Panel, Plug, 'click'
J1-1	DC+	1	Power input, +28V nominal	3A maximum current
J1-2	0V	2	Power return	3A maximum current
J1-3	GND1	3	Communication channel 1 GND	Common for TX/RX for comm. channel 1;
J1-4	TX1/TX1-	4	RS232 TX1, or RS422 TX1-	Dual purpose comm. channel 1
J1-5	TX1+	5	RS422 TX1+	Used if RS422 interface is selected for comm. channel 1
J1-6	RX1/RX1-	6	RS232 RX1, or RS422 RX1-	Dual purpose, comm. Channel 1
J1-7	RX1+	7	RS422 RX1+	Used if RS422 interface is selected for comm. Channel 1
J1-8	TX2/TX2-	8	RS232 TX2, or RS422 TX2-	Dual purpose comm. Channel 2
J1-9	RX2/RX2-	9	RS232 RX2, or RS422 RX2-	Dual purpose, comm. Channel 2
J1-10	GND2	10	Communication channel 2 GND	Common for TX/RX for comm. Channel 2;
J1-11	GND3	11	Communication channel 3 GND	Common for TX/RX for comm. Channel 3;

<sup>&</sup>lt;sup>7</sup> With compliant line connectors attached.



File: <b>PS-RMU-S-1680-A_1</b>	Author(s): TW	Authorised: TW	Rev. Date: 11.3.14	Page 2-6

<sup>&</sup>lt;sup>8</sup> Refer to manufacturer for details.



# Black Opal Xtreme Air 19 Airborne Special Flat Panel Display System

No.	Name	Pin Marking	Purpose	Notes for Harness
			ower & Comms Connection	n (cont'd)
J1-12	TX3/TX2+	12	RS232 TX3, or RS422 TX2+	Dual purpose comm. Channel 2/3. RS422 (on comm. Channel 2) and RS232 (comm. channel 3) are mutually exclusive as they share common pins.
J1-13	RX3/RX2+	13	RS232 RX3, or RX422 RX2+	Dual purpose comm. Channel 2/3. RS422 (on comm. Channel 2) and RS232 (comm. channel 3) are mutually exclusive as they share common pins.
J2: S	D Video In/Out Co	nnection:	Connector, MilSpec, 38999/2 screw-on, 22 Way	4WC35SN, 13-35, Panel, Socket, 'click'
J2-1	Y1/CVBS1	1	Video channel 1 luma/composite signal	75 ohm terminated
J2-2	C1/CVBS5	2	Video channel 1 chroma signal/second composite signal for channel 1	75 ohm terminated
J2-3	Y2/CVBS2	3	Video channel 2 luma/composite signal	75 ohm terminated
J2-4	C2/CVBS6	4	Video channel 2 chroma signal/second composite signal for channel 2	75 ohm terminated
J2-5	Y3/CVBS3	5	Video channel 3 luma/composite signal	75 ohm terminated
J2-6	C3/CVBS7	6	Video channel 3 chroma signal/second composite signal for channel 3	75 ohm terminated
J2-7	Y4/CVBS4	7	Video channel 4 luma/composite signal	75 ohm terminated
J2-8	C4/CVBS8	8	Video channel 4 chroma signal/second composite signal for channel 4	75 ohm terminated
J2-9	Out1	9	CVBS output (SD), or Y/G output (HD/PC)	Video output, 75 ohm impedance.
J2-10	GND_Out1	10	Video output 1 GND	Return for Out1
J2-11	Out2	11	Luma output (S-VIDEO), or Pb/B output (HD/PC)	Video output, 75 ohm impedance.



File: <b>PS-RMU-S-1680-A_1</b>	Author(s): TW	Authorised: TW	Rev. Date: 11.3.14	Page 2-7



# Black Opal Xtreme Air 19 Airborne Special Flat Panel Display System

externally control the backlight (if enabled)  J3: HD Video Connection: Connector, MilSpec, 38999/24WC35PN, 13-35, Panel, Plug, 'click' screw-on, 22 Way  J3-1 GREENA1 1 Analog video input: 75 ohm terminated. Use as Green for	No.	Name	Pin Marking	Purpose	Notes for Harness
J2-13 Out3 13 Chroma output (S-Video), or Pr/R output (HD/PC) J2-14 GND_Out3 14 Video output 3 GND Return for Out3 J2-15 GND1 15 Video channel 1 GND Common for Y1 and C1 J2-16 GND2 16 Video channel 2 GND Common for Y2 and C2 J2-17 GND3 17 Video channel 3 GND Common for Y3 and C3 J2-18 GND4 18 Video channel 4 GND Common for Y3 and C3 J2-19 HS_Out 19 Horizontal sync output Synchronisation signal if sync-on-green or sync-on-Y is not used. J2-20 VS_Out 20 Vertical sync output Synchronisation signal if sync-on-green or sync-on-Y is not used. J2-21 Sync_GND 21 HS_VS Ground Common for HS and VS signals J2-22 Dimming 22 Analog Input, used to externally control the backlight (if enabled)  J3: HD Video Connection: Connector, MilSpec, 38999/24WC35PN, 13-35, Panel, Plug, 'click' screw-on, 22 Way  J3-1 GREENA1 1 Analog video input: GreenA1 / YA1 / YA1 / CVBSA1 input  Analog video input: BlueA1 / PbA1 / YA2 / CVBSA2 input  J3-3 BLUEA1 3 Analog video input: BlueA1 / PbA1 / YA2 / CVBSA2 input  J3-4 GREENA1_GND 2 GND return for pin 1  J3-3 BLUEA1 3 Analog video input: BlueA1 / PbA1 / YA2 / CVBSA2 input  J3-4 GREENA1_GND 3 Analog video input: BlueA1 / PbA1 / YA2 / CVBSA2 input  J3-6 FOR Y, Pr), Y for s-video (with pin 5 1 and 5 for Y, Pr), Y for s-video (with pin 6 for chroma), or as a CVBS input			J2: S	D Video In/Out Connection	(cont'd)
J2-14 GND_Out3 14 Video output 3 GND Return for Out3  J2-15 GND1 15 Video channel 1 GND Common for Y1 and C1  J2-16 GND2 16 Video channel 2 GND Common for Y2 and C2  J2-17 GND3 17 Video channel 3 GND Common for Y3 and C3  J2-18 GND4 18 Video channel 4 GND Common for Y4 and C4  J2-19 HS_Out 19 Horizontal sync output Synchronisation signal if sync-on-green or sync-on-Y is not used.  J2-20 VS_Out 20 Vertical sync output Synchronisation signal if sync-on-green or sync-on-Y is not used.  J2-21 Sync_GND 21 HS,VS Ground Common for HS and VS signals  J2-22 Dimming 22 Analog Input, used to externally control the backlight (if enabled)  J3: HD Video Connection: Connector, MilSpec, 38999/24WC35PN, 13-35, Panel, Plug, 'click' screw-on, 22 Way  J3-1 GREENA1 1 Analog video input: GreenA1 / YA1 / YA1 / CVBSA1 input  Analog video input: GreenA1 / YA1 / YA1 / CVBSA1 input  J3-2 GREENA1_GND 2 GND return for pin 1  J3-3 BLUEA1 3 Analog video input: BlueA1 / PbA1 / YA2/ CVBSA2 input  J3-5 For heterminated. Use as Blue for PC input (with pins 1 and 5). Also can be used as Pb for component (with pins 1 and 5 for Y, Pr), Y for s-video (with pin 9 for chroma), or as a CVBS input	J2-12	GND_Out2	12	Video output 2 GND	Return for Out2
J2-15 GND1 15 Video channel 1 GND Common for Y1 and C1  J2-16 GND2 16 Video channel 2 GND Common for Y2 and C2  J2-17 GND3 17 Video channel 3 GND Common for Y2 and C2  J2-18 GND4 18 Video channel 4 GND Common for Y4 and C4  J2-19 HS_Out 19 Horizontal sync output Synchronisation signal if sync-on-green or sync-on-Y is not used.  J2-20 VS_Out 20 Vertical sync output Synchronisation signal if sync-on-green or sync-on-Y is not used.  J2-21 Sync_GND 21 HS,VS Ground Common for HS and VS signals  J2-22 Dimming 22 Analog Input, used to externally control the backlight (if enabled)  J3: HD Video Connection: Connector, MilSpec, 38999/24WC35PN, 13-35, Panel, Plug, 'click' screw-on, 22 Way  J3-1 GREENA1 1 Analog video input: GreenA1 / YA1 / YA1 / CVBSA1 input 75 ohm terminated. Use as Green for PC input (with pins 3 and 5 for Pr, Pb), Y for s-video (with pin 3 and 5 for Y, Pb), Y for s-video (with pin 1 and 5 for Y, Pr), Y for s-video (with pin 1 and 5 for Y, Pr), Y for s-video (with pin 1 and 5 for Y, Pr), Y for s-video (with pin 1 and 5 for Y, Pr), Y for s-video (with pin 1 and 5 for Y, Pr), Y for s-video (with pin 1 and 5 for Y, Pr), Y for s-video (with pin 9 for chroma), or as a CVBS input	J2-13	Out3	13	• • •	Video output, 75 ohm impedance.
J2-16 GND2  J2-17 GND3  J2-18 GND4  J2-18 GND4  J2-19 HS_Out  J2-19 HS_Out  J2-20 VS_Out  J2-21 Sync_GND  J2-22 Dimming  J2-22 Dimming  J2-23 Dimming  J3-3 GREENA1_GND  J3-3 BLUEA1  J3-3 BLUEA1  J3-4 GND4  J2-24 GND4  J3-16 GND4  J3-17 Video channel 2 GND  Video channel 3 GND  Video channel 4 GND  Common for Y2 and C2  Common for Y3 and C3  Common for Y4 and C4  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Synchronisation signal if sync-on-year or synchronisation signal if sync-	J2-14	GND_Out3	14	Video output 3 GND	Return for Out3
J2-17   GND3   17   Video channel 3 GND   Common for Y3 and C3     J2-18   GND4   18   Video channel 4 GND   Common for Y4 and C4     J2-19   HS_Out   19   Horizontal sync output   Synchronisation signal if sync-on-green or sync-on-Y is not used.     J2-20   VS_Out   20   Vertical sync output   Synchronisation signal if sync-on-green or sync-on-Y is not used.     J2-21   Sync_GND   21   HS,VS Ground   Common for HS and VS signals     J2-22   Dimming   22   Analog Input, used to externally control the backlight (if enabled)   0 to 32V range, maximum detected input is 60V.     J3: HD Video Connection: Connector, MilSpec, 38999/24WC35PN, 13-35, Panel, Plug, 'click' screw-on, 22 Way     J3-1   GREENA1   Analog video input: GreenA1 / YA1 / YA1 / CVBSA1 input   T5 ohm terminated. Use as Green for PC input (with pins 3 and 5 for Pr, Pb), Y for s-video (with pin 7 for chroma), or as a CVBS input     J3-3   BLUEA1   3   Analog video input: BlueA1 / PbA1 / YA2 / CVBSA2 input   T5 ohm terminated. Use as Blue for PC input (with pins 1 and 5 for Y, Pr), Y for s-video (with pin 1 and 5 for Y, Pr), Y for s-video (with pin 1 and 5 for Y, Pr), Y for s-video (with pin 9 for chroma), or as a CVBS input	J2-15	GND1	15	Video channel 1 GND	Common for Y1 and C1
J2-18 GND4       18       Video channel 4 GND       Common for Y4 and C4         J2-19 HS_Out       19       Horizontal sync output       Synchronisation signal if sync-on-green or sync-on-Y is not used.         J2-20 VS_Out       20       Vertical sync output       Synchronisation signal if sync-on-green or sync-on-Y is not used.         J2-21 Sync_GND       21       HS,VS Ground       Common for HS and VS signals         J2-22 Dimming       22       Analog Input, used to externally control the backlight (if enabled)       0 to 32V range, maximum detected input is 60V.         J3: HD Video Connection: Connector, MilSpec, 38999/24WC35PN, 13-35, Panel, Plug, 'click' screw-on, 22 Way       75 ohm terminated. Use as Green for PC input (with pins 3 and 5). Also can be used as Y for component (with pins 3 and 5 for Pr, Pb), Y for s-video (with pin 7 for chroma), or as a CVBS input         J3-3 BLUEA1       3       Analog video input: BlueA1 / PbA1 / YA2/ CVBSA2 input       75 ohm terminated. Use as Blue for PC input (with pins 1 and 5). Also can be used as Pb for component (with pins 1 and 5 for Y, Pr), Y for s-video (with pin 9 for chroma), or as a CVBS input	J2-16	GND2	16	Video channel 2 GND	Common for Y2 and C2
J2-19 HS_Out  19 Horizontal sync output  Synchronisation signal if sync-on-green or sync-on-Y is not used.  J2-20 VS_Out  20 Vertical sync output  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Synchronisation signal if sync-on-green or sync-on-Y is not used.  Common for HS and VS signals  Dimming  22 Analog Input, used to externally control the backlight (if enabled)  J3: HD Video Connection: Connector, MilSpec, 38999/24WC35PN, 13-35, Panel, Plug, 'click' screw-on, 22 Way  J3-1 GREENA1  1 Analog video input: GreenA1 / YA1 / YA1 / CVBSA1 input  To ohm terminated. Use as Green for PC input (with pins 3 and 5). Also can be used as Y for component (with pins 3 and 5 for Pr, Pb), Y for s-video (with pin 7 for chroma), or as a CVBS input  J3-3 BLUEA1  3 Analog video input: BlueA1 / PbA1 / YA2 / CVBSA2 input  3 Analog video input: BlueA1 / PbA1 / YA2 / CVBSA2 input  3 Analog video input: BlueA1 / PbA1 / YA2 / CVBSA2 input  3 Analog video input: BlueA1 / PbA1 / YA2 / CVBSA2 input  4 Analog video input: BlueA1 / PbA1 / YA2 / CVBSA2 input  5 ontherminated. Use as Blue for PC input (with pins 1 and 5). Also can be used as Pb for component (with pins 1 and 5 for Y, Pr), Y for s-video (with pin 9 for chroma), or as a CVBS input	J2-17	GND3	17	Video channel 3 GND	Common for Y3 and C3
J2-20 VS_Out  20 Vertical sync output  Synchronisation signal if sync-on-green or sync-on-Y is not used.  J2-21 Sync_GND  21 HS,VS Ground  Common for HS and VS signals  J2-22 Dimming  22 Analog Input, used to externally control the backlight (if enabled)  J3: HD Video Connection: Connector, MilSpec, 38999/24WC35PN, 13-35, Panel, Plug, 'click' screw-on, 22 Way  J3-1 GREENA1  Analog video input: GreenA1 / YA1 / YA1/ CVBSA1 input  GREENA1_GND  GREENA1_GND  GREENA1  Analog video input: BlueA1 / PbA1 / YA2/ CVBSA2 input  J3-3 BLUEA1  Analog video input: BlueA1 / PbA1 / YA2/ CVBSA2 input  J3-6 ohm terminated. Use as Blue for PC input (with pins 1 and 5). Also can be used as Pb for component (with pins 1 and 5 for Y, Pr), Y for s-video (with pin 9 for chroma), or as a CVBS input	J2-18	GND4	18	Video channel 4 GND	Common for Y4 and C4
J2-21 Sync_GND 21 HS,VS Ground Common for HS and VS signals  J2-22 Dimming 22 Analog Input, used to externally control the backlight (if enabled) 0 to 32V range, maximum detected input is 60V.  J3: HD Video Connection: Connector, MilSpec, 38999/24WC35PN, 13-35, Panel, Plug, 'click' screw-on, 22 Way  J3-1 GREENA1 1 Analog video input: GreenA1 / YA1 / YA1 / CVBSA1 input 75 ohm terminated. Use as Green for PC input (with pins 3 and 5). Also can be used as Y for component (with pins 3 and 5 for Pr, Pb), Y for s-video (with pin 7 for chroma), or as a CVBS input  J3-3 BLUEA1 3 Analog video input: BlueA1 / PbA1 / YA2 / CVBSA2 input with pins 1 and 5 for Y, Pr), Y for s-video (with pin 1 and 5 for Y, Pr), Y for s-video (with pin 9 for chroma), or as a CVBS input	J2-19	HS_Out	19	Horizontal sync output	, , , , , , , , , , , , , , , , , , , ,
J2-22 Dimming  22 Analog Input, used to externally control the backlight (if enabled)  J3: HD Video Connection: Connector, MilSpec, 38999/24WC35PN, 13-35, Panel, Plug, 'click' screw-on, 22 Way  J3-1 GREENA1  1 Analog video input: GreenA1 / YA1 / YA1/ CVBSA1 input  CVBSA1 input  J3-2 GREENA1_GND  2 GND return for pin 1  J3-3 BLUEA1  3 Analog video input: BlueA1 / PbA1 / YA2/ CVBSA2 input  75 ohm terminated. Use as Green for PC input (with pins 3 and 5). Also can be used as Y for component (with pins 3 and 5 for Pr, Pb), Y for s-video (with pin 7 for chroma), or as a CVBS input  3 Analog video input: BlueA1 / PbA1 / YA2/ CVBSA2 input  3 Analog video input: BlueA1 / PbA1 / YA2/ CVBSA2 input  4 Analog video input: BlueA1 / PbA1 / YA2/ CVBSA2 input  5 Ohm terminated. Use as Blue for PC input (with pins 1 and 5). Also can be used as Pb for component (with pins 1 and 5 for Y, Pr), Y for s-video (with pin 9 for chroma), or as a CVBS input	J2-20	VS_Out	20	Vertical sync output	
### Externally control the backlight (if enabled)  ### J3: HD Video Connection: Connector, MilSpec, 38999/24WC35PN, 13-35, Panel, Plug, 'click' screw-on, 22 Way  ### J3-1 GREENA1	J2-21	Sync_GND	21	HS,VS Ground	Common for HS and VS signals
J3-1 GREENA1  1 Analog video input: GreenA1 / YA1 / YA1/ CVBSA1 input  3 and 5 for Pr, Pb), Y for s-video (with pin 7 for chroma), or as a CVBS input  3 Analog video input: BlueA1 / PbA1 / YA2/ CVBSA2 input  3 Analog video input: BlueA1 / PbA1 / YA2/ CVBSA2 input  3 Analog video input: BlueA1 / PbA1 / YA2/ CVBSA2 input  4 Analog video input: BlueA1 / PbA1 / YA2/ CVBSA2 input  5 Ohm terminated. Use as Blue for PC input (with pins 1 and 5). Also can be used as Pb for component (with pins 1 and 5 for Y, Pr), Y for s-video (with pin 9 for chroma), or as a CVBS input	J2-22	Dimming	100	externally control the	0 to 32V range, maximum detected input is 60V.
GreenA1 / YA1 / YA1/ CVBSA1 input  GreenA1 / YA1 / YA1/ CVBSA1 input  GREENA1_GND  GREENA1_GND  GREENA1_GND  GREENA1_GND  GREENA1_GND  Analog video input: BlueA1 / PbA1 / YA2 / CVBSA2 input  J3-3  BLUEA1  Analog video input: BlueA1 / PbA1 / YA2 / CVBSA2 input  input  GREENA1_GND  Analog video input: BlueA1 / PbA1 / YA2 / CVBSA2 input  input  GREENA1_GND  GREENA1_GND  Analog video input: BlueA1 / PbA1 / YA2 / CVBSA2 input  input (with pins 1 and 5). Also can be used as Pb for component (with pins 1 and 5 for Y, Pr), Y for s-video (with pin 9 for chroma), or as a CVBS input	J3: H	D Video Connection	on: Connect		PN, 13-35, Panel, Plug, 'click' screw-on,
J3-3 BLUEA1  Analog video input: BlueA1 / PbA1 / YA2/ CVBSA2 input  T5 ohm terminated. Use as Blue for PC input (with pins 1 and 5). Also can be used as Pb for component (with pins 1 and 5 for Y, Pr), Y for s-video (with pin 9 for chroma), or as a CVBS input	J3-1	GREENA1		GreenA1 / YA1 / YA1/	PC input (with pins 3 and 5). Also can be used as Y for component (with pins 3 and 5 for Pr, Pb), Y for s-video (with pin
/ PbA1 / YA2/ CVBSA2 input (with pins 1 and 5). Also can be used as Pb for component (with pins 1 and 5 for Y, Pr), Y for s-video (with pin 9 for chroma), or as a CVBS input	J3-2	GREENA1_GND	2	GND return for pin 1	
J3-4 BLUEA1_GND 4 GND return for pin 3	J3-3	BLUEA1	3	/ PbA1 / YA2/ CVBSA2	input (with pins 1 and 5). Also can be used as Pb for component (with pins 1 and 5 for Y, Pr), Y for s-video (with pin 9
	J3-4	BLUEA1_GND	4	GND return for pin 3	



File: <b>PS-RMU-S-1680-A_1</b>	Author(s): TW	Authorised: TW	Rev. Date: 11.3.14	Page 2-8



# Black Opal Xtreme Air 19 Airborne Special Flat Panel Display System

No.	Name	Pin Marking	Purpose	Notes for Harness			
J3: HD Video Connection (cont'd)							
J3-5	REDA1	5		75 ohm terminated. Use as Red for PC input (with pins 1 and 3). Also can be used as Pr for component (with pins 1 and 3 for Y, Pb), Y for s-video (with pin 11 for chroma), or as a CVBS input			
J3-6	REDA1_GND	6	GND return for pin 5				
J3-7	REDA2	7	Analog video input: RedA2 / PrA2 / CA1/ CVBSA4 input	75 ohm terminated. Use as Pr for HD input (with pins 9 and 11). Also can be used as Red (with pins 9 and 11), C for s-video (with pin 1 for luma), or as a CVBS input			
J3-8	REDA2_GND	8	GND return for pin 7				
J3-9	BLUEA2	9	Analog video input: BlueA2 / PrA2 / CA2/ CVBSA5 input	75 ohm terminated. Use as Pb for HD input (with pins 7 and 11). Also can be used as Blue (with pins 7 and 11), C for s-video (with pin 3 for luma), or as a CVBS input			
J3-10	BLUEA2_GND	10	GND return for pin 9				
J3-11	GREENA2	11	Analog video input: GreenA2 / YA2/ CA3/ CVBSA6 input	75 ohm terminated. Use as Y for HD input (with pins 7 and 9). Also can be used as Green (with pins 7 and 9), C for s-video (with pin 5 for luma), or as a CVBS input			
J3-12	GREENA2_GND	12	GND return for pin 11				
J3-13	DDC_SCL	13	DDC channel clock (RGB1)	Optional			
J3-14	DDC_SDA	14	DDC channel data (RGB1)	Optional			
J3-15	HSA1	15	Horizontal Sync, for RGB A1	TTL level			
J3-16	VSA1	16	Vertical Sync, for RGB A1	TTL level			
J3-17	GNDA1	17	GND for HSA1, VSA1				
J3-18	HSA2	18	Horizontal Sync, for RGB A2	TTL level			
J3-19	VSA2	19	Vertical Sync, for RGB A2	TTL level			



File: <b>PS-RMU-S-1680-A_1</b>	Author(s): TW	Authorised: TW	Rev. Date: 11.3.14	Page 2-9



# Black Opal Xtreme Air 19 Airborne Special Flat Panel Display System

No.	Name	Pin Marking	Purpose	Notes for Harness		
J3: HD Video Connection (cont'd)						
J3-20	GNDA2	20	GND for HSA2, VSA2			
J3-21	DDC_+5V	21	DDC channel +5V	Optional		
J3-22	DDC_GND	22	DDC channel GND	Optional		
		J4: Ear	th Point Connection: M5 th	readed stud		
J5:	Misc. Connection	(optional):	Connector, MilSpec, 38999/ screw-on, 22 Way	24WC35PA, 13-35, Panel, Plug, 'click'		
J5-1	TX+	1	Ethernet TX+ pin 1	Fully protected against transients.		
J5-2	TX-	2	Ethernet TX- pin 2	Fully protected against transients.		
J5-3	RX+	3	Ethernet RX+ pin 3	Fully protected against transients.		
J5-4	RX-	4	Ethernet RX- pin 6	Fully protected against transients.		
J5-5	SHIELD	5	Shield for Ethernet (chassis)	tied to chassis		
J5-6	USB_+5V	6	USB Pin 1	factory configured, ESD protection only		
J5-7	USBDATA	7	USB Pin 2	factory configured, ESD protection only		
J5-8	USB_+DATA	8	USB Pin 3	factory configured, ESD protection only		
J5-9	USB_GND	9	USB Pin 4	factory configured, ESD protection only		
J5-10	Audio_L_in	10	Audio input, Left	Fully protected against transients.		
J5-11	Audio_R_in	11	Audio input, Right	Fully protected against transients.		
J5-12	Audio_L_out	12	Audio output, Left	Fully protected against transients.		
J5-13	Audio_R_out	13	Audio output, Right	Fully protected against transients.		
J5-14	Audio GND.	14	Common for audio	tied to chassis		
J5-15	PS2_DATA	15	PS2 pin 1, or USBOTG D+	factory configured, ESD protection only		
J5-16	PS2_GND	16	PS2 pin 3, or USBOTG GND	factory configured, ESD protection only		
J5-17	PS2_VCC	17	PS2 pin 4, or USBOTG VBUS	factory configured, ESD protection only		
J5-18	PS2_CLK	18	PS2 pin 5, or USBOTG D-	factory configured, ESD protection only		
J5-19	Audio_GND_IN	19		tied to chassis		
J5-20	Audio_GND_OUT	20		tied to chassis		



File: <b>PS-RMU-S-1680-A_1</b>	Author(s): TW	Authorised: TW	Rev. Date: 11.3.14	Page 2-10



# Black Opal Xtreme Air 19 Airborne Special Flat Panel Display System

No.	Name	Pin Marking	Purpose	Notes for Harness			
	J5: Misc. Connection (cont'd)						
J5-21	spare1	21	unused, or Ethernet LED+ for SPD LED, or USBOTG ID	factory configured, ESD protection only			
J5-22	spare2	22	unused, or Ethernet LED+ for LINK LED.	factory configured, ESD protection only			
		J6: SDI	Input #1 Connection: Conn	nector, BNC			
	SDI In1 SDI input #1 for SD-SDI, 75 ohm BNC. Cable must comply with HD-SDI (3G-SDI optional) loss requirements of SMPTE 292M.						
		J7: SDI	Input #2 Connection: Conn	nector, BNC			
	SDI In2  SDI input #2 for SD-SDI, 75 ohm BNC. Cable must comply with ID-SDI (3G-SDI optional) loss requirements of SMPTE 292M.						
	J8: SDI Output #1 Connection: Connector, BNC						
			75 ohm BNC. Cable must comply with loss requirements of SMPTE 292M.				
		J9: SDI	Output #2 Connection: Con	nector, BNC			
	SDI Out2  Generated SDI output (SD-SDI, HD-SDI (3G-SDI optional)  Generated SDI output (SD-Ioss requirements of SMPTE 292M.						
J10: Heater Power Connection: Connector, MilSpec, 38999/24WA35PN, 13-35, Panel, Plug, 'click' screwon, 6 Way							
J10-1	Heater Power1 +	1	Power input, +28V nominal	5A maximum current			
J10-2	Heater Power1 -	2	Power return	5A maximum current			
J10-3	Heater Power2 +	3	Power input, +28V nominal	5A maximum current			
J10-4	Heater Power2 -	4	Power return	5A maximum current			
J10-5	Display Power +	5	Power input, +28V nominal	5A maximum current			
J10-6	Display Power -	6	Power return	5A maximum current			



File: <b>PS-RMU-S-1680-A_1</b>	Author(s): TW	Authorised: TW	Rev. Date: 11.3.14	Page 2-11




## Black Opal Xtreme Air 19 Airborne Special Flat Panel Display System

#### 3 SET-UP

#### 3.1 Mounts

The unit has two mounting methods:

- 1. Panel Mount: eight 5.5 diameter holes, 4 per side.
- 2. Side Mount: two M4 tapped holes, 8mm deep, on each side of the rear section.



Authorised: TW

#### 3.2 Connections

File: PS-RMU-S-1680-A\_1

The unit has ten connection points located on the rear:

Connector J1, the Power & Comms connection;

Connector J2, the SD Video In/Out connection;

Author(s): TW

Connector J3, the HD Video connection;

Connector J4, the Earth Point connection;





## Black Opal Xtreme Air 19 Airborne Special Flat Panel Display System

Connector J5, the Miscellaneous connection (optional);

Connector J6, the SDI Input #1 connection;

Connector J7, the SDI Input #2 connection;

Connector J8, the SDI Output #1 connection;

Connector J9, the SDI Output #2 connection; and

Connector J10, the Heater Power connection.




Figure 3-2: Connections

#### 3.3 Set-up Procedure

**CAUTION:** 

User-supplied cables must be correctly wired (see list of Connector/Pin Details).

Ensure that external power is within the range specified herein.

Ensure that external power is OFF before proceeding with set-up.





### Black Opal Xtreme Air 19 Airborne Special Flat Panel Display System

- Mount the unit to the vehicle or platform, using one of the mounting methods provided.
- Connect the earth point on the unit to an appropriate point on the vehicle.
- Connect the required cables for video in/out to the unit and to the external imaging system(s).
- Connect the required power/data cable to the unit and to the external power source, and to the communication data source.
- Connect the required cable for heater power to the unit and to the external power source.

#### 3.4 Heating and Cooling

The unit contains internal heating and cooling mechanisms that are triggered at certain internal temperatures.

The approximate warm-up rate is 17s/°C (e.g. with starting internal temperature of -40°C, unit will power up in about 11 minutes; with starting internal temperature of -25°C, unit will power up in about 7 minutes).

Once the unit has warmed it will operate normally provided that the ambient temperature stays within the specified operating temperature range.

The operating procedures, internal temperatures and resulting operating conditions are shown in the following table.

Ambient Temp. (°C)	Procedure	Internal Temp. (°C)	Operating Condition
< -40	do not attempt to operate unit		
-40 to 0	de-ice unit prior to start-up	≤ 0	unit will not power up; heater on
	2	> 0	unit will power up; internal convection on
0 to +55	none	≥ 10	heater off
		≥ 55	backlight reduces
+55 to +70	provide forced air cooling (e.g. fan)		
> +70	do not attempt to operate unit	≥ 75	unit will not power up



File: <b>PS-RMU-S-1680-A_1</b>	Author(s): TW	Authorised: TW	Rev. Date: 11.3.14	Page 3-3



### Black Opal Xtreme Air 19 Airborne Special Flat Panel Display System

#### **4 OUTLINE DRAWING**




Figure 4-1: Outline Drawing



A Division of Laserdyne Pty Ltd A.C.N. 053 743 132

17 Production Ave Molendinar Queensland 4214 Australia

Tel: (07) 5594 9772 Int'l Tel: 61 7 5594 9772 Fax: (07) 5594 9981 Int'l Fax: 61 7 5594 9981

email: laserdyne@laserdyne.com.au website: www.laserdyne.com.au

The information contained herein is proprietary to Laserdyne Pty Ltd. No part of this work may be reproduced or copied in any way without prior written permission of Laserdyne Pty Ltd. Note: specifications herein are subject to change without notice.

